

⑫

EUROPEAN PATENT APPLICATION

⑲ Application number: **88115230.0**

⑤① Int. Cl. 4: **H04N 17/02 , H04N 9/73 , G09G 1/28**

⑳ Date of filing: **16.09.88**

③① Priority: **26.10.87 US 113022**

④③ Date of publication of application:
03.05.89 Bulletin 89/18

⑥④ Designated Contracting States:
DE FR GB NL

⑦① Applicant: **TEKTRONIX, INC.**
Howard Vollum Park 14150 Karl Braun Drive
Lake Oswego Oregon 97077(US)

⑦② Inventor: **McManus, Paul Albert**
240 N. W. Gleneagle Drive
Sherwood Oregon 97140(US)
Inventor: **Beaton, Robert John**
12905 S. W. Rita Drive
Beaverton Oregon 97005(US)

⑦④ Representative: **Liska, Horst, Dr. et al**
Patentanwälte H. Weickmann, Dr. K. Fincke,
F.A. Weickmann, B. Huber, Dr. H. Liska, Dr. J.
Prechtel Möhlstrasse 22 Postfach 86 08 20
D-8000 München 86(DE)

⑤④ Video monitor color control system.

⑤⑦ A video monitor color control system including means for calibrating the intensity response of CRT phosphor sets to each of a plurality of electron gun control levels. Provided is a processor (24) that generates a sequence of discrete DAC signals, each DAC signal identifying an electron gun and a DAC value for driving the electron gun at a selected control level. Also provided is a monitor driver (22) connected to the processor (24) and to the monitor (20) and controllable in response to a DAC signal for driving the electron gun identified by the DAC signal at the control level identified by the DAC signal. The driven electron gun excites the associated phosphor set. A sensor (28) is provided for detecting the luminous intensity level of the phosphor excited by the electron gun, and for converting the detected intensity into a representative signal. The processor (24) receives for each discrete DAC signal the representative signals produced by the sensor and generates a look-up table for each gun defining intensity levels for each of the plurality of electron gun control levels.




FIG. 1

VIDEO MONITOR COLOR CONTROL SYSTEM

Technical Field

This invention pertains to a system for accurately controlling video monitor color characteristics.

Background Information

Video monitors comprising cathode-ray tubes (CRT's) are widely used display devices. Color CRT displays are especially useful means for conveying graphic information. Generally, a color CRT display includes three electron guns, each gun controllable to excite an associated red, green or blue phosphor set carried on the CRT screen. In some applications, such as graphic arts, advertising, textile design, etc., color CRT displays are relied upon to display colors having specific colorimetric parameters, so that the identical color can be reproduced with other media (paints, inks, dyes, etc.) using those same colorimetric parameters. Such parameters may be the well-known XYZ tristimulus values as defined by the International Commission on Illumination or CIE.

Disclosed in a copending patent application of Murch, et al., entitled, "Display-Based Color System", is a useful system for organizing colors into a perceptually uniform color space having coordinates that are related to the CIE tristimulus values XYZ. Also disclosed is a method for transforming a point in that color space (as defined by the color space coordinates) into suitable notation for displaying that point (i.e., color) on a CRT display. To this end, the point is transformed into a corresponding rgb intensity vector. An rgb intensity vector is a 3-element vector denoting the relative intensity contribution of each CRT phosphor set required for displaying a selected color. To display a color represented by an rgb intensity vector, it is necessary to convert the rgb intensity vector into associated "DAC values." DAC values are scaled numerical values (usually ranging from 0-255) corresponding to the electron gun control levels required to drive the associated phosphor set at various luminous intensities.

In order to utilize rgb intensity vectors, or for otherwise producing colorimetrically accurate displays, the CRT display must be calibrated. That is, the DAC-value/phosphor intensity relationship must be precisely determined.

Summary of the Invention

This invention is directed in part to a system for calibrating the intensity response of CRT monitor phosphor sets to each of a plurality of electron gun control levels. Specifically provided is a processor that generates a sequence of discrete DAC signals. Each DAC signal identifies an electron gun and a DAC value for driving the electron gun at a selected control level. Also provided is a monitor driver that is connected to the processor and to the monitor and is controllable, in response to a DAC signal, for driving the electron gun identified by the DAC signal at the control level that is identified by the DAC signal. The driven electron gun excites an associated phosphor set. A sensor is provided for detecting the luminous intensity level of the phosphor set excited by the electron gun, and for converting the detected intensity into a representative signal. The processor receives the representative signal produced by the sensor and stores, as intensity data, each DAC value along with the corresponding phosphor set intensity level.

As another aspect of this invention, the processor processes the intensity data to generate functional approximation thereof for constructing look-up tables defining intensity levels for each of the plurality of DAC values.

As another aspect of this invention, the system is operable for utilizing the detected luminous intensity levels for generating matrices suitable for reversibly transforming rgb intensity vectors into corresponding XYZ tristimulus values.

As another aspect of this invention, the video monitor control system is operable for accurately reproducing a color sample on the video monitor.

Brief Description of the Drawings

Fig. 1 is a diagram of the system of the present invention.

Fig. 2 is a flow chart depicting the sequence of events for calibrating a video monitor in accordance with the invention.

Fig. 3 is a flow chart depicting the sequence of events for generating matrices suitable for reversibly transforming rgb intensity vectors into corresponding XYZ tristimulus values.

Fig. 4 is a diagram of an alternative embodiment of the system useful for detecting colorimetric data from a color sample and for accurately duplicating the color on a video monitor.

Fig. 5 is a flow chart depicting the sequence of events for detecting colorimetric data from a color sample and for duplicating the color on a video monitor.

Detailed Description of the Preferred Embodiments

Referring to Fig. 1, a preferred embodiment of the present invention is employed for calibrating a video monitor 20. The monitor 20 to be calibrated may be any color CRT device. As is known, the monitor includes three electron guns, each gun corresponding to a red, green or blue phosphor set carried on the CRT screen 21.

Each electron gun delivers a beam of electrons to the screen to excite the associated phosphor set. The phosphor set glows at a luminous intensity level that corresponds to the beam current or control level of the gun. The beam is raster-scanned over the screen in response to conventional beam deflection mechanisms. The monitor 20 is driven by a display generator system or monitor driver 22. The monitor and monitor driver can be any suitable color graphics system such as a Tektronix 4125 Color Graphics Workstation. Further, although the discussion hereafter identifies a separate main computer 24, it is contemplated that all of the described functions of the computer may be carried out by the processor sets incorporated into the Color Graphics Workstation. As a result, such a workstation will have self-calibration capability. It is also pointed out that the video monitor color control system of the present invention is useful for calibrating any personal computer monitor driven with a color graphics display generator.

The monitor driver 22 receives control signals from the a computer 24 via a conductor 26. The control signals, hereafter referred to as "DAC signals", are coded digital signals identifying a control level for driving a particular electron gun. The monitor driver decodes the signals and drives the gun accordingly.

The main computer 24, such as a Compaq personal computer manufactured by Compaq Computer Company, includes a processor that is programmed to generate a sequence of DAC signals, and to supply those signals to the monitor driver 22. Specifically, as mentioned above, each DAC signal sent to the monitor identifies an electron gun to be addressed by the monitor driver, and indicates the DAC value corresponding to a particular gun control level. Typically, DAC values range in integer increments from 0 to 255.

For each DAC signal, the monitor driver 22 directs the monitor 20 to produce a full screen display of the color that results when the signaled electron gun is driven at the signaled DAC value. As each distinct DAC signal is sent to the monitor, the computer 24 signals a sensor 28 to supply the computer with a number of luminous intensity level readings detected from the CRT screen. In this regard, the sensor 28 is any suitable photometer or radiometer responsive to the monitor screen luminosity to produce a representative analog electrical signal.

Preferably, the monitor screen 21 is shielded 29 to eliminate ambient light effects on the sensor.

A sensor controller 30 is interconnected between the sensor 28 and the computer 24 to facilitate communication therebetween. The sensor controller includes an analog-to-digital (A/D) converter for reducing the sensor readings to representative digital signals. Further, the sensor controller includes a microprocessor such as an Intel 8751, which is programmed to supply the digital intensity signals to the main computer via a conductor 32 when signaled by the main computer. Several intensity level readings are delivered to the computer for each DAC signal. The computer averages and stores the readings.

After DAC-value/intensity data has been obtained for all three guns, the data is processed, as described more fully below, to construct a DAC-value/intensity look-up table for each gun. The look-up tables are tabulations of every single DAC value along with an associated phosphor set luminous intensity level. The look-up tables are thereafter available to convert rgb intensity vectors into the appropriate DAC values, or to convert the DAC values of a color into its rgb intensity vector.

Turning to Fig. 2, depicted there is a flow chart corresponding to the computer program used for operating the system of Fig. 1. Specifically, the computer 24 receives as input the DAC value step size, the upper and lower DAC value limits, and the number of guns. The DAC value step size indicates the increment between each DAC value sent to the monitor driver via each DAC signal. Rapid calibration is

achieved if the DAC value step size is 5; however, any step size may be selected.

Lower limit and upper limit DAC value constants are also established. Specifically, the upper limit DAC value constant is established at 255. The lower limit constant is established at a value nearest to 0, which will yield an integer multiple of the DAC value step size between the upper and lower limits. For instance, for a DAC value step size of 25, the lower limit is established at 5. Establishing the lower limit as just described ensures that the intensity level for the highest DAC value, 255, will always be detected.

The number of guns input to the computer indicates whether a monochrome (1 gun) or color (3 gun) monitor is being calibrated. This discussion assumes that a color monitor is being calibrated, although monochrome monitors may be likewise calibrated.

After establishing communications files between the computer 24 and the monitor driver 22, and between the computer and the sensor controller 30, the sequence of DAC signals is sent by the computer 24 to the monitor driver, 22. In the preferred embodiment, each DAC signal is transmitted in a coded form comprising ASCII characters that identify the DAC signal as a sequence of three elements respectively corresponding to the DAC values for the electron guns associated with the red, green and blue phosphors. Two of the three elements are established at DAC values equal to 0, and the remaining element is the DAC value to be applied to the associated electron gun.

After each DAC signal is transmitted to the monitor a "sample" signal is transmitted to the sensor controller communication file. The sensor controller reads the "sample" signal and loads the communication file with a digital intensity level reading that was obtained, via the A/D converter in the sensor controller 30, from the continuously applied sensor output. The content of the communication file is read by the computer, which then signals for another reading. This sampling process is repeated for the same DAC signal until several (preferably 10) intensity level readings are obtained and averaged.

The averaged intensity readings are stored as part of an array of DAC-value/intensity levels. The computer next generates and sends to the monitor driver another DAC signal corresponding to the next DAC value step for the same gun signaled in the prior DAC signal. It is pointed out that the sequence of DAC signals may be sent in ascending or descending order of DAC values between the upper and lower DAC value limits. It has been found, however, that phosphor persistence may influence intensity readings if the monitor is driven with descending DAC value steps. Accordingly, it is preferred that the DAC signal sequence be sent to the monitor in order of ascending DAC values.

After intensity levels for all DAC values of all guns have been collected (the DAC-value/intensity data hereafter referred to as the "intensity data"), the low end of the intensity data is analyzed to delete that portion of the data wherein the intensity levels are indistinguishable from noise. That is, during manufacture and set up of each monitor, the CRT electron guns are over-biased to ensure that a zero drive voltage applied to the guns yields no phosphor glow. Thus, it is desirable to delete the low DAC values having no effect of the phosphor intensity because of the over-biasing (i.e., the DAC values "producing" only noise). To this end, the intensity levels of the two lowest DAC values are compared. If the difference in the levels does not exceed a threshold value t , the lower level is discarded and the remaining level is then compared with the next higher level. This comparison process continues for increasing DAC values until the difference between compared intensity levels exceeds the threshold t , at which point the intensity data will be free of all meaningless data.

The threshold value, t , is established as the detectable difference in the power or intensity function of the CRT corresponding to the change in DAC values (i.e., gun control levels) between each DAC signal.

The intensity data, comprising as it does a set of ordered pairs, is amenable to curve fitting techniques for providing a simple analytical expression of the DAC-value/intensity relationship. Preferably, the data is processed by the technique known as the least-squares fit method, wherein the coefficients of the polynomial function

$$y = a_0 + a_1x + a_2x^2 + \dots + a_mx^m \quad (1)$$

are obtained by solving the system of $m + 1$ equations:

$$na_0 + a_1 \sum X_i + a_2 \sum X_i^2 + \dots + a_m \sum X_i^m = \sum Y_i;$$

$$a_0 \sum X_i + a_1 \sum X_i^2 + a_2 \sum X_i^3 + \dots + a_m \sum X_i^{m+1} = \sum X_i Y_i;$$

$$a_0 \sum X_i^m + a_1 \sum X_i^{m+1} + a_2 \sum X_i^{m+2} + \dots + a_m \sum X_i^{2m} = \sum X_i^m Y_i$$

It has been found that acceptable curve fitting results are obtained when the degree, m , of the

polynomial is between 5 and 7.

Using the calculated coefficients of the polynomial function of equation (1), a look-up table for each electron gun is next generated and stored by the computer. Specifically, the look-up table is generated by solving the polynomial function for each single DAC value between upper limit (255) and the lower limit remaining after the noise data deletions are made. Usually, the remaining lower limit DAC value will be in the range of 25-30. It is important to note that the look-up table comprises intensity levels for every single DAC value, and not just for the DAC value steps for which the intensity data was originally collected.

It is contemplated that the look-up tables could be constructed without processing the intensity data as just described. For instance, useful look-up tables may be constructed by acquiring intensity level readings for every DAC-value (i.e., DAC value step size = 1). However, greater precision is found with the data processing technique just described.

As another aspect of this invention, the system is readily adaptable to generate a matrix useful for precisely converting rgb intensity vectors into corresponding CIE tristimulus values XYZ. That matrix is hereafter referred to as the RGB-to-XYZ matrix and denoted [A]. Similarly, the system also generates a matrix known as the XYZ-to-RGB matrix for converting the XYZ tristimulus values of a color into a corresponding rgb intensity vector. The XYZ-to-RGB matrix is denoted $[A^{-1}]$.

With reference to Figs. 1 and 3, to construct the RGB-to-XYZ matrix, the computer is supplied with two sets of data, one data set is referred to as the specified RGB-to-XYZ matrix and denoted [SA]. This data is generated through spectroradiographic analysis of the monitor at the time of manufacture. The specified RGB-to-XYZ matrix is a 3-by-3 matrix, the elements of which represent the relative intensity contributions of the red, green and blue phosphors (columns) to the XYZ tristimulus values (rows) determined when the phosphors are excited to full intensity. A useful explanation of the CIE system and the related tristimulus values XYZ is provided in "Principles of Color Technology", 2nd ed. 1981, by Billmeyer and Saltzman.

The second data set supplied to the computer is a three element vector denoted [P], the elements of which represent the peak luminous intensity level of the red, green and blue phosphors as detected at the time the specified RGB-to-XYZ matrix data was compiled.

As an important aspect of this invention, the system processes the input data in conjunction with intensity level readings to generate a corrected RGB-to-XYZ matrix, which reflects the true phosphor luminance characteristics of the monitor, as opposed to those characteristics specified by the manufacturer. In this regard, it can be appreciated that heavy use, vibrations, etc., can vary the luminous characteristics of a particular monitor relative to the specified characteristics. Accordingly, employing the system of the present invention to account for these variations yields a "corrected" RGB-to-XYZ matrix. This corrected matrix, denoted [A], is important for generating colors on the monitor that have the colorimetric parameters desired.

Corrected RGB-to-XYZ matrix construction commences with the computer generating a series of three DAC signals. The first DAC signal instructs the monitor driver to drive the "red" electron gun to produce a peak intensity red phosphor glow. That is, the red electron gun is driven at the maximum DAC value, 255. After the first DAC signal is transmitted to the monitor driver, the intensity level reading is sampled from the monitor screen and stored in the computer as described earlier.

The second and third DAC signals similarly signal peak intensity blue phosphor glow and peak green phosphor glow, respectively. As above, the peak intensity level readings for these phosphors are sampled and stored. It can be appreciated that the peak intensity levels may also be obtained by reference to the look-up tables described earlier.

The sampled peak intensity levels for each phosphor is compared with (i.e., divided into) its counterpart of the specified vector [P]. This comparison yields a correction factor vector $[P_c]$, the three elements of which represent, in decimal form, the variation of each actual phosphor peak intensity level from that specified. Accordingly, when the specified RGB-to-XYZ matrix is multiplied by the correction factor vector $[P_c]$, the corrected RGB-to-XYZ matrix is formed.

As noted earlier, the corrected RGB-to-XYZ matrix is useful for transforming an rgb intensity vector into its corresponding XYZ tristimulus values.

The corrected RGB-to-XYZ matrix is next inverted to yield the 3-by-3 XYZ-to-RGB matrix, $[A^{-1}]$. As noted earlier, the XYZ-to-RGB matrix is useful for transforming the tristimulus values of a color into its corresponding rgb intensity vector for the CRT.

As another aspect of this invention, the video monitor color control system is readily adaptable for accurately reproducing a color sample on a video monitor. With reference to Figs. 4 and 5, and as described in more detail below, the sensor 28 and a color filter wheel 40 are employed to detect the luminous characteristics of a uniform color sample 42. These characteristics are transformed, using an XYZ-to-RGB matrix, into an rgb intensity vector for the video monitor. The rgb intensity vector is converted via

the above-described look-up tables into the corresponding DAC values and the sampled color is displayed on the monitor screen 21.

Turning to the particulars of the color duplication process just outlined, the color wheel 40 is used to provide the sensor 28 with the luminance levels of the red, green and blue light that is reflected from the color sample 42. The light passing through the red, green and blue filters will hereafter be referred to as the red, green and blue primaries. The color wheel is a circular arrangement of three color filters and one clear space. The color wheel is selectively rotatable by known means. It is contemplated that other mechanisms interchanging for color filters may be substituted for the color wheel.

The color wheel 40 is analyzed with conventional spectrophotometric means to establish the colorimetric properties of each filter. In this regard, the red, green and blue filters are each illuminated by a standard CIE illuminant and the primary light transmitted therethrough is analyzed to determine the relative contribution of each primary to the CIE XYZ tristimulus values of the illuminant. This data is assembled into a color filters matrix denoted [F]. The color filters matrix is a 3-by-3 matrix with elements representing the relative intensity contributions of the red, green and blue primaries (columns) to the XYZ values (rows) of the illuminant.

Preferably, the color filters matrix is normalized so that the Y tristimulus value of the illuminant will equal 1. As noted in the referenced patent application by Murch, et al., this normalization is useful for correlating the Y tristimulus value with a color parameter of the CIE system known as the metric lightness function. The metric lightness function is a useful means of describing the lightness of a color.

The color filters matrix data is next processed to account for differences between the illuminant used to establish the matrix and the "reference white" light, which is the light used for illuminating the color sample. To this end, a white reflecting surface, such as white paper, is positioned between the color sample 42 and the color wheel 40. The reference light reflected from the paper passes through the red, green and blue filters of the rotating color wheel 40. The computer 24 instructs the sensor controller 30 to provide luminance intensity level readings for each of the red, green and blue primaries passing through the filters. These readings are arranged in a reference white rgb primary vector, $[r_w]$, the three elements of which represent the relative red, green and blue primary luminance contributions of the reference white.

The rgb primary vector $[r_w]$ for the reference white is next multiplied by the Y row of the color filter matrix [F] to yield the Y tristimulus value corresponding to the reference white, Y_w , or

$$Y_w = [r_w] \times [F]$$

All of the elements of the color filters matrix [F] are divided by the reference white tristimulus value Y_w to yield a new color filters matrix $[F_w]$ which is weighted for the reference white light under which the color sample is detected.

With the weighted color filter matrix $[F_w]$ constructed as just described, the luminance characteristics of the color sample 42 are detected for reproduction of the color on the monitor screen. More particularly, the color wheel is positioned between the color sample 42 and the sensor 28. The computer 24 is controlled to collect, via the sensor controller 30, luminance intensity levels for the red, green and blue primaries as the color wheel is rotated. The sampled intensity level data is arranged into a sample rgb primary intensity vector, denoted $[r_s]$. The three elements of the sample rgb primary vector represent the relative luminance contributions of the primaries of the sampled color.

The sample rgb primary intensity vector is next multiplied with the weighted color filter matrix $[F_w]$ to yield the tristimulus values X_s , Y_s , Z_s , for the sampled color.

The tristimulus values X_s , Y_s , Z_s for the sampled color are next multiplied by the XYZ-to-RGB matrix $[A^{-1}]$, described above, to yield for the sampled color the corresponding rgb intensity vector in terms of the rgb phosphors (hereafter referred to as the phosphor rgb intensity vector).

The phosphor rgb intensity vector is compared with the above-described look-up tables earlier to yield the three DAC values for each gun that correspond to the phosphor rgb intensity vector of the sample color. Driving the electron guns with these DAC values produces on the video monitor a color that duplicates, in colorimetric terms, the sample color.

While preferred embodiments of the invention have been illustrated and described, it will be appreciated that various changes can be made therein without departing from the spirit and scope of the invention as defined in the claims.

Claims

1. A system for calibrating the intensity response of CRT monitor phosphor sets to each of a plurality of electron gun control levels, wherein each phosphor set is excitable by an associated electron gun, comprising:
 - (a) processing means for generating a sequence of discrete DAC signals, each DAC signal identifying an electron gun and a DAC value for driving the electron gun at a selected control level;
 - (b) monitor drive means connected to the processing means and to the monitor and controllable in response to a DAC signal for driving the electron gun identified by the DAC signal at a control level identified by the DAC signal; and
 - (c) sensor means for detecting the luminous intensity level of the phosphor excited by the electron gun that is driven by the monitor drive means, and for generating a signal representative of the detected phosphor intensity level, the processing means connected to the sensor means for receiving for each discrete DAC signal the representative signals produced by the sensor means, and for storing as intensity data each DAC value with the associated detected phosphor intensity level.
2. The system of claim 1 wherein the processing means includes means for generating and storing look-up tables defining intensity levels for each of the electron gun control levels as a continuous function derived from the stored intensity data.
3. A method for calibrating the luminous intensity response of CRT phosphor sets to each of a plurality of electron gun control levels, wherein each phosphor set is excitable by an associated electron gun, the method comprising the steps of:
 - (a) generating a sequence of discrete DAC signals, each DAC signal identifying an electron gun and DAC value for driving the electron gun at a selected control level;
 - (b) driving, in response to each DAC signal, the electron gun identified by the DAC signal at the control level identified by the DAC signal;
 - (c) detecting the luminous intensity level of the phosphor set excited by the driven electron gun; and
 - (d) storing the detected luminous intensity level and DAC value for each DAC signal.
4. The method of claim 3 further including the step of processing the stored intensity level and DAC values to construct a tabulation defining intensity levels for each of the electron gun control levels as a continuous function.
5. A system for generating a matrix suitable for reversibly transforming rgb intensity vectors into CIE XYZ tristimulus values, wherein rgb intensity vectors denote the relative intensity contribution of CRT phosphor sets in displaying a selected color on a CRT, the system comprising:
 - (a) processing means for
 - (1) receiving and storing first and second data, the first data representative of predetermined relative intensity contributions of the red, green and blue phosphor sets to the X, Y and Z tristimulus values resulting when the three phosphor sets are excited to full intensity, the second data representative of predetermined relative luminous intensity level contributions of the red, green and blue phosphor sets when each phosphor set is excited to full intensity;
 - (2) generating a sequence of discrete DAC signals, each DAC signal identifying a phosphor set and a DAC value corresponding to the full luminous intensity level of the phosphor set;
 - (b) monitor drive means connected to the processing means and to the CRT and controllable in response to a DAC signal for driving the phosphor set identified by the DAC signal at the luminous intensity level identified by the DAC signal; and
 - (c) sensor means for detecting the luminous intensity level of each phosphor set as each phosphor set is driven at the full luminous intensity level and for generating a signal representative of the detected phosphor intensity level, the processing means being connected to the sensor means for receiving and storing as third data the representative signals generated by the sensor for each phosphor set, and for comparing the second and third data to determine correction data, the processing means applying the correction data to the first data to generate the matrix.
6. The system of claim 5 wherein the processing means includes means for inverting the matrix.
7. A method for generating matrices suitable for reversibly transforming rgb intensity vectors into CIE XYZ tristimulus values, wherein rgb intensity vectors denote the relative intensity contribution of CRT phosphor sets in displaying a selected color on a CRT, the method comprising the steps of:

(a) receiving and storing first and second data, the first data representative of predetermined relative intensity contributions of the red, green and blue phosphor sets to the X, Y and Z tristimulus values resulting when the phosphor sets are excited to full intensity, the second data representative of predetermined relative luminous intensity level contributions of the red, green and blue phosphor sets when each phosphor set is excited to full intensity;

(b) generating a sequence of discrete DAC signals, each DAC signal identifying a phosphor set and a DAC value corresponding to the full luminous intensity level of the phosphor set;

(c) driving in response to each DAC signal the phosphor set identified by the DAC signal at the luminous intensity level identified by the DAC signal;

(d) detecting the luminous intensity level of the phosphor set as each phosphor set is driven at the luminous intensity level of the DAC signal;

(e) comparing the detected luminous intensity levels for each phosphor set to the second data to determine correction data; and

(f) transforming the first data into the matrix by applying the correction data to the first data.

8. The method of claim 7 including the step of inverting the matrix.

9. A method for reproducing a color sample on a video monitor wherein the color sample is definable by a primary rgb intensity vector denoting the relative red, green and blue luminance intensity levels of the color sample, and wherein the video monitor is controllable to produce a color in accordance with a phosphor rgb intensity vector denoting the relative values of the luminance intensity levels of the red, green and blue phosphor sets of the monitor screen, the method comprising the steps of:

(a) generating a matrix for converting primary rgb intensity vectors into XYZ tristimulus values;

(b) detecting the primary rgb intensity vector for the color sample;

(c) multiplying the detected primary rgb intensity vector with the matrix to generate the XYZ tristimulus values of the color sample;

(d) transforming the XYZ tristimulus values of the color sample into the corresponding phosphor rgb intensity vector; and

(e) controlling the video monitor to display the color corresponding to the phosphor rgb intensity vector of the color sample.

10. A system for reproducing a color sample on a video monitor wherein the color sample is definable by a primary rgb intensity vector denoting the relative red, green and blue luminance intensity levels of the color sample, and wherein the video monitor is controllable to produce a color in accordance with a phosphor rgb intensity vector denoting the relative values of the luminance intensities of the red, green and blue phosphor sets of the monitor screen, the system comprising:

(a) sensing means for detecting the primary intensity vector of the color sample;

(b) processing means for

(1) generating a matrix for converting primary rgb intensity vectors into XYZ tristimulus values;

(2) multiplying the detected primary rgb intensity vector of the sampled color with the matrix to generate the XYZ tristimulus values of the color sample;

(3) transforming the XYZ tristimulus values of the color sample into a corresponding phosphor rgb intensity vector; and

(c) driving means for controlling the video monitor to display the color corresponding to the phosphor rgb intensity vector of the color sample.




FIG. 1




FIG. 4




FIG. 2




FIG. 3




FIG. 5



European Patent
Office

EUROPEAN SEARCH REPORT

Application number

DOCUMENTS CONSIDERED TO BE RELEVANT			EP 88115230.0
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int. Cl.4)
A	US - A - 4 631 576 (ST. JOHN) * Fig. 4; column 4, line 53 - column 5, line 19 * --	1,2	H 04 N 17/02 H 04 N 9/73 G 09 G 1/28
A	US - A - 4 379 292 (MINATO) * Abstract; fig. 3 * --	1,2	
A	US - A - 4 700 218 (THOMSEN) * Abstract; fig. 1 * --	1,2	
A	GB - A - 2 169 773 (SONY) * Abstract; fig. 1 * ----	1,2	
			TECHNICAL FIELDS SEARCHED (Int. Cl.4)
			H 04 N 9/00 H 04 N 17/00 G 09 G 1/00
The present search report has been drawn up for all claims			
Place of search VIENNA		Date of completion of the search 23-01-1989	Examiner BENISCHKA
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document</p>			